

LED controller

RGB controller, with RF wireless remote, adopts the advanced micro control unit. Which is used to control different color changes of a variety of LED lights such as point source of LED light. LED flexible strip, LED wall washer lamp, glass curtain wall light, LED lighting module, advertisement box of LED lights and so on; It is convenient to connect, and easy to use; According to the actual need of customers, it can carry out jumpy changing, gradual changing, stroboflash and other effects of change!

Technical Parameter:

Voltage:DC5-24V

Current:10A*3

Power:12V=360W

Power Dissipation:<0.5W

Size: 110*90*25mm

Connecting mode: common anode

Remote: RF wireless remote and keys on the controller

Work Temperature:-20~+60

Remote Distance:<30Meters

Direction for use

- 1、 Connect the load wire at first, then the power wire ; Never connect two wires directly in case of short circuit ;
- 2、 According to "mode" key to choose the different changing mode every time, when the key is pressed, the effect is changed, functional changes have been listed as follows ;
- 3、 Press "S/B" key can change every effect's speed or brightness, " S/B+" add one when you press the button every time, but " S/B-" will subtract one.

Mod e			Mod e		
1	Static red	brightness adjustable	is	12	Red and green gradual changing Speed is adjustable
2	Static green	brightness adjustable	is	13	Green and bleu gradual changing Speed is adjustable
3	Static blue	brightness adjustable	is	14	Red quickly change Speed is adjustable
4	Static red and green	brightness adjustable	is	15	Green quickly change Speed is adjustable
5	Static red and blue	brightness adjustable	is	16	Blue quickly change Speed is adjustable
6	Static green and blue	brightness adjustable	is	17	Red and green quickly change at the same Speed is adjustable
7	Three color jumpy changing	Speed adjustable	is	18	Red and blue quickly change at the same Speed is adjustable
8	seven color jumpy changing	Speed adjustable	is	19	Green and blue quickly change at the same Speed is adjustable
9	Three color gradual changing	Speed adjustable	is	20	R G B quickly change Speed is adjustable
10	seven color jumpy changing	Speed adjustable	is	21	Mode 8 and mode 10 Speed is unadjustable
11	Red and blue gradual changing	Speed adjustable	is	22	RGB gradual changing at the same Speed is adjustable

Conjunction diagram

